GSM independent Multi-function alarm

User Manual

Quad-band

This product use military technology GSM module with multi sensor components, also have remote sound pickup function, can be installed in home, companies,shops and warehouse, this product compact size, voice clear, long standby time, simple operation, stable performance, without install, remote control etc.,

Product view:

Usage:

Please open the back cover and you can see SIM card holder. insert SIM card with right direction as instruction, the lights flash 1 time, means the TC-100 has been switched on, the light will flash 3 times about after 30 seconds,that's means ready for work.

Past the host and magnet box on door and door case.

Switch language

Send **LAG1** change the language to Chinese.
Send **LAG2** change the language to English.
Send **LAG3** change the language to Russian.

Function Settings:

Send ***GDM1*** start voice sensor alarm ,when sound around ,TC-100 will call the sender.
Send ***GDM2*** stop voice control.
Send ***GDM4*** start magnetic sensor alarm, when the door was opened or closed ,the product will sent SMS or call the sender.
Send ***GDM5*** stop magnetic sensor control.
Send **TIM**** set voice control call back interval.
Send ***LBS*** report GSM base station ID and location map link.
send **MOD1** the alarm mode will change as send SMS first, and then call.
send **MOD2** the alarm mode will change as only call.
Send **MOD3** the alarm mode will change as Send SMS only.
Send **DSP** can inquire the current state

If you want TC-100 answer incoming call automatically, please binding number:
send SMS **HM1 (2,3,4,5)**,setting the SMS sender as emergency number.when the sender call TC-100, it will auto-answer this call.The emergency number can be up to 5 .

Note:

Boot this machine must be inserted SIM card.

Please inserted the SIM card when charge.

The new machines need to be recharged 2-3 hours before first use. Please use our distribute charger to protect host.

Standby time: 160-240 hours . depending on the local network signal strength may be.

if the product can't Auto-Answer: please confirm whether banding emergency number.

Network type:
GSM850/900MHz/DCS1800/1900MHz

Accessories:
Host 1
Magnet bos 1
Charger 1
USB Charging Cable 1